

HIGH EFFICIENCY 500W FM TRANSMITTER EM 500 HE DIG PLUS COMPACT

The 500W FM transmitter **EM 500 HE DIG PLUS COMPACT** has been created by the OMB center of development for high efficiency transmitters. Its flexibility, quality, compactness, together with its low electrical consumption make the **EM 500 HE DIG PLUS COMPACT** one of the best offered on the market today. This transmitter can be supplied with an internal digital stereo generator board (60dB separation).



MAIN ADVANTAGES

- Typical AC efficiency >73% and typical RF efficiency of 82%.
- An amplifying module of 600W with MOSFET technology.
- Memory recording of events.
- Speed control of cooling fans according to temperature of power modules so as to optimize consumption and to decrease acoustic contamination.
- Advanced protection against load mismatches without transmission cuts and fast protection in case of excessive reflected power and/or excessive input power.
- Analog telemetry, digital remote control and telemetry RS232, remote control by opened/closed contacts
- Low pass filter, Mains EMI filter and internal single-phase transient suppressor.
- Automatic power reduction at night.
- Automatic power reduction in case of high temperature, the equipment returns automatically to its rated power value when the temperature reaches back an average value.
- Automatic power reduction in case of excessive reflected power.
- Automatic voltage control for efficiency optimization.
- AES/EBU input with automatic selection of audio signal optional.

broadcast your _ world

GENERAL CHARACTERISTICS

FREQUENCY RANGE	87.5-108MHz
FM MODULATION	75KHz (adjustable) peak deviation. Mono 180kF3E and Stereo 256kF3E
AUDIO/MPX INPUT LEVEL	-3.5 to +12.5dBm @ 75KHz deviation
AUDIO INPUT CONNECTORS	XLR(F)
AUX. CHANNEL INPUT LEVEL (RDS/SCA)	7.5KHz deviation: -12.5 to 3.5dBm 2KHz deviation: -24 to -8dBm
AUX. CHANNEL INPUT IMPEDANCE	10KOhm
MODULATION DISTORTION	7.5KHz deviation: <0.05%, 0.02% typical 2KHz deviation: <0.2%, 0.05% typical
MONO S/N RATIO	30 to 20000Hz: >76dB, 86dB typical CCIR: >75dB, 81dB typical
STEREO S/N RATIO	30 to 20000Hz: >72dB, 77dB typical CCIR: >68dB, 72dB typical
AUDIO CHANNELS BANDWIDTH	30 to 15000Hz \pm 0.1dB
PRE-EMPHASIS TIME CONSTANT	Selectable, 0/50/75 microseconds
NOMINAL RF OUTPUT POWER	500W
CONSUMPTION	~750VA at 500W output power
TOTAL EFFICIENCY	>73% typical
RF EFFICIENCY	80%
TRANSMITTER TUNING STEPS	10/100KHz
OUTPUT POWER ALC STABILITY	\pm 3%
HARMONICS AND SPURIOUS EMISSIONS	<80dBc
RF OUTPUT IMPEDANCE	50 Ω
RF OUTPUT CONNECTOR	N type, 7/16"(F) optional
RF SAMPLER CONNECTOR	BNC type
POWER SUPPLY	Single phase 110-230Vac \pm 15% 50/60Hz
CONSUMPTION	713VA (500W)
OPERATING TEMPERATURE RANGE	0 to 40°C recommended, -10 to +55° max.
RELATIVE HUMIDITY	Up to 95% not condensed
DIMENSIONS	2 standard rack units of 19"
WEIGHT	11Kg

** The images and/or technical specifications are subject to change without previous notice.*

broadcast your _ world